




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H02K 17/06		A1	(11) International Publication Number: WO 99/63642
			(43) International Publication Date: 9 December 1999 (09.12.99)
(21) International Application Number: PCT/US99/11235		(81) Designated States: AE, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CU, CZ, DE, DK, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, UA, UG, UZ, VN, YU, ZA, ZW, ARIPO patent (GH, GM, KE, LS, MW, SD, SL, SZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).	
(22) International Filing Date: 20 May 1999 (20.05.99)			
(30) Priority Data: 09/090,658 4 June 1998 (04.06.98) US			
(71) Applicant: EMERSON ELECTRIC CO. [US/US]; 8000 W. Florissant, St. Louis, MO 63136 (US).			
(74) Agent: WHEELLOCK, Bryan, K.; Suite 1400, 7733 Forsyth Boulevard, St. Louis, MO 63105 (US).		Published With international search report. With amended claims.	

(54) Title: SINGLE PHASE THREE SPEED MOTOR WITH SHARED WINDINGS

(57) Abstract

A single phase, three-speed Pole-changing electric motor has a stator and a rotor rotatably mounted within the stator. The stator includes a core having a plurality of slots, and a plurality of windings in the slots for operating at least three speeds. The windings are configured and arranged so that a substantial portion of the windings used in operating at one speed are used in operating at another speed. The reconnection of windings for different speeds is simple and easy to implement, for example with an external timer, switch, or relay.



Ref. #35

EMER 2616

Renyan William Fei, et al

SN Not Assigned Yet

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakhstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

PATENT

SINGLE PHASE THREE SPEED MOTOR
WITH SHARED WINDINGS

FIELD OF THE INVENTION

This invention relates to a single phase three-speed induction motor, and in particular to such a motor in which a substantial portion of the windings are shared for operation at different speeds.

5 BACKGROUND OF THE INVENTION

Multispeed pole-changing single phase motors typically comprise separate windings for operation at each speed. For example, in the case of a three speed induction motor, the stator might include an eight-pole main winding for operation at low speed, a six-pole main winding for operation at medium speed, and a four-pole main winding for operation at high
10 speed. A separate auxiliary winding is often provided for starting the motor. This auxiliary winding is typically a four-pole winding for so-called "hard" starting. In these motors, only a small portion of the windings, the coils under one pole are shared for operation at different speeds. The application of different approaches for winding sharing in the prior art is limited by complicated reconnection which substantially increases the motor cost.

15 To accommodate a large number of windings in the limited slot size the windings typically are made of copper, which is relatively expensive.

SUMMARY OF THE INVENTION

The present invention relates to a three speed, pole changing single phase capacitor-start or split phase induction motor in which a substantial portion of the windings for the various speeds are shared through a simple winding reconnection. This leaves more room in the slots, and allows bulkier but less expensive materials (such as aluminum) to be used for the windings. More particularly, the motor of the present invention comprises a stator, and a rotor rotatably mounted within the stator. The stator comprises a core, which is conventionally made of a stack plurality of laminations of a magnetically permeable material. The core has a plurality of slots therein for receiving the windings. According to the present invention, these windings include a first winding, having four coil sections; a second winding having two coil sections; a third winding having two coil sections; a fourth winding having six coil sections; and an auxiliary starting winding having six coil sections.

Shared winding techniques have been proposed before. However, the feasibility of such techniques largely depends on the simplicity of the winding reconnection. The winding configuration of the present invention used the existing starting switch and requires only one additional single pole, single throw contact from a switch outside the motor, such as a timer, relay, electronic switch, etc. As compared with separate winding motors this is very easy and inexpensive to implement.

The windings are connectable to operate in a four pole high speed configuration, a six pole medium speed configuration, and an eight pole low speed configuration. More particularly the first winding, the second winding, and the third winding are arranged in the slots so that they can be connected to operate in a four pole conventional configuration. The second winding and the third winding are also arranged in the slots so that they can be connected to operate in an eight pole consequent configuration. The fourth winding is arranged in the slots so that it can be connected to operate in a six pole conventional configuration. Lastly, the auxiliary winding is arranged in the slots so that it can be operated in a six pole conventional configuration during start-up of the motor.

Because in this preferred embodiment the windings for eight pole operation are fully shared with the windings for four pole operation, there is extra room in the stator slots. This allows a bulkier but lighter material, such as aluminum, to be used for the windings instead of a more compact but heavier materials such as copper. Thus the resultant motor is significantly lighter, not just because of the elimination of a separate winding for operation in the eight pole-mode, but because the space freed up by the elimination of the separate eight pole winding allows a lighter material to be used for the remaining windings. Furthermore, aluminum is considerably less expensive than copper, so the motor is less expensive to manufacture.

These and other features and advantages will be in part apparent, and in part pointed out hereinafter.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a schematic diagram of a three speed single phase electric motor constructed according to the principles of this invention;

Fig. 2 is a winding diagram of the motor;

Fig. 3 is a winding diagram of the motor, illustrating the first, second, and third windings connected to operate in a four pole (high speed) mode;

Fig. 4 is a winding diagram of the motor, illustrating the second and third windings connected to operate in an eight pole (low speed) mode;

Fig. 5 is a winding diagram of the motor, illustrating the fourth winding connected to operate in a six pole (medium speed) mode; and

Fig. 6 is a winding diagram of the motor, illustrating the auxiliary winding connected to operate in a six pole starting mode.

Corresponding reference numerals indicate corresponding parts throughout the several views of the drawings.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

A three speed, single phase electric motor constructed according to the principles of the present invention, indicated generally as 20, is shown schematically in Fig. 1. The motor 20 comprises a stator of conventional construction formed of a stack of laminations of a magnetically permeable material, with a plurality of slots for holding windings.

The motor 20 comprises a first winding 22 having four coil sections, a second winding 24 having two coil sections, a third winding 26 having two coil sections, and a fourth winding 28 having six coil sections. The motor also has an auxiliary winding 30 having six coil sections for start up. As shown in Fig. 1, the first coil 22, the second coil 24, and the third coil 26 are arranged to be connected to a power supply to operate in a conventional four pole (high speed) mode. The second coil 24 and the third coil 26 are also arranged to be connected to a power supply to operate in a consequent eight pole (low speed) mode. The fourth winding 28 is configured to be connected to a power supply to operate in a conventional six pole (medium speed) mode. Lastly, the auxiliary winding 30 is configured to be connected to a power supply during start-up with the fourth winding 28, to start the motor.

In this preferred embodiment, all of the windings for operating in the eight pole mode (windings 24 and 26) are windings that are also used to operate in the four pole mode, no separate winding is provided to operate in the eight pole mode. This means that there is additional room in the slots in the stator as compared to other three speed motors. This

additional room facilitates manufacture of the motor, and it allows bulkier but less expensive materials such as aluminum to be used for the windings instead of the more expensive copper to reduce the material cost and the motor weight.

The configuration of the winding to operate in the four pole (high speed); six pole
5 (medium speed), and eight pole (low speed) modes, is achieved by switches 32, 34 and 36, which are preferably external to the motor.

Switch 32 operates between a first 6 pole position, and a second 4 pole/8 pole position. Switch 34 operates between a first 4 pole position and second 8 pole position. Switch 36 operates between a first 4 pole position and a second 6 pole/8 pole position. A
10 starting switch 38 is also provided to temporarily connect the six pole main winding 28 and the auxiliary winding 30 to power to start the motor.

The physical arrangement of the windings in the slots in the stator is best shown in Figs. 2-6. As shown in Figs 2-6, the stator core 40 has a plurality of slots (a total of 34 as shown). The first winding 22 comprises four coil sections 22a, 22b, 22c, and 22d, connected
15 in series such that in 4-pole operational mode when the coil sections 22a and 22c form north poles, the coil sections 22b and 22d form south poles. The second winding 24 comprises two coil sections 24a and 24b, connected in series. The third winding 26 comprises two coil sections 26a and 26b, connected in series. In 4-pole operational mode, the winding 24 and 26 are in parallel and both of them together are in series with the winding 22. The winding 24 is
20 positioned in the slots, such that coil section 24a is aligned with coil section 22d and coil section 24b is aligned with coil section 22b. The coil sections 24a and 24b are configured, so that when they are powered in 4-pole operational mode, they will have the same polarity as the coil sections 22d and 22b with which they are aligned. Likewise, the coil sections 26a and 26b are aligned with coil sections 22c and 22a, respectively. The coil sections 26a and 26b are
25 configured, so that when they are powered in 4-pole operational mode, they will have the same polarity as the coil sections 22c and 22a with which they are aligned. In this configuration, the first, second, and third windings cooperate to operate in a conventional four pole mode, with the coil sections 22a and 26b forming a north pole, the coil sections 22d and 24a forming a south pole, coil sections 22c and 26a forming a north pole, and coil sections
30 22b and 24b forming a south pole.

The first, second, and third windings are connected for operation the four pole (high speed) mode, when switch 32 is in the 4 pole/8 pole position, switch 34 is in the 4 pole position, and switch 36 is in the 4 pole position. This configuration is shown in Fig. 3, in which the coil sections forming a north pole are hatched and the coil sections forming a south
35 pole are cross-hatched.

The second and third windings 24 and 26 are also connected in series, and when

powered in series, the coil sections 24a and 24b of the second winding, and coil sections 26a and 26b of the third winding all form poles in the same direction, in this case north, which forms an eight pole consequent winding.

When the second and third windings 24 and 26 are connected and powered in series,
5 the coil sections 24a and 24b of the second winding and the coil sections 26a and 26b of the third winding all form poles with the same polarity, (for example all north), which forms an eight pole consequent winding.

The fourth winding 28 comprises winding sections 28a, 28b, 28c, 28d, 28e, and 28f.
The coil sections are configured and connected so that coil sections 28a, 28c, and 28e form
10 south poles, and so that winding sections 28b, 28d, and 28f form north poles. When the winding 28 is connected to power, the winding operates in a six pole conventional mode.

The fourth winding is connected for operation in the six pole (medium speed) mode
when switch 32 is in the 6 pole mode, switch 36 is in the 6/8 pole mode, and switch 34 is in
either the 4 pole or 8 pole position. The coil sections are arranged around the circumference
15 of the stator to form alternating poles. This configuration is shown in Fig. 5, in which coil sections forming a north pole are hatched and coil section forming a south pole are cross-hatched.

Lastly the auxiliary winding 30 comprises coil sections 30a, 30b, 30c, 30d, 30e, and
30f. The coil sections are configured and connected so that winding sections 30a, 30c, and
20 30e form south poles, and so that winding sections 30b, 30d, and 30f form north poles. When the auxiliary winding 30 and the fourth winding 28 are connected to power, (caused by the operation of the starting switch 38) the winding operates in a six pole conventional mode to start the motor. The coil sections are arranged around the circumference of the stator to form alternating poles. This configuration is shown in Figs. 5 and 6 in which coil sections forming
25 a north pole are hatched, and the coil sections forming a south pole are cross-hatched. During starting the 6 pole main winding 28 and the 6 pole auxiliary winding 30 are both energized. They are shifted in space by 90 electrical degrees or 30 mechanical degrees.

What is claimed is:

1. A single phase, three-speed induction motor comprising a stator and a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and a plurality of windings in the slots for operating at at least three different pole speeds, at least one of the windings being used in its entirety to operate at at least two of the at least
5 three different pole speeds.
2. A single phase, three speed induction motor comprising a stator having a plurality of slots and a rotor rotatably mounted within the stator, the stator comprising a plurality of windings for operating at at least three speeds, including a first winding having two coil sections and a second winding having two coil sections, the windings arranged in the slots of
5 the stator so that the coil sections from each winding alternate, the entire first and second windings being connectable to operate in a four pole conventional mode and being alternatively connectable to operate in an eight pole consequent mode.
3. A single phase, three speed induction motor comprising a stator, and rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots and a plurality of windings in the slots for operating the motor at at least three speeds, the windings including at least two windings each having at least one coil section, arranged to be
5 selectively connected in their entireties to form a first number of conventional magnetic poles, and a second number of consequent magnetic poles.
4. A single-phase, three speed induction motor comprising a stator, a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and a plurality of windings in the slots configurable to operate in four, six, and eight pole modes, the windings comprising:
5 a first winding having four coil sections;
 a second winding having two coil sections;
 a third winding having two coil sections;
 a fourth winding having six coil sections;
 the first, second, and third windings being positioned and connectable to operate in a
10 four-pole conventional mode, and the second and third windings being positioned and connectable to operate in an eight-pole consequent mode.

5. The motor according to claim 4 further comprising an auxiliary winding having six coil sections for starting the motor.

6. A single-phase, three speed induction motor comprising a stator, a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and a plurality of windings in the slots configurable to operate in four, six, and eight pole modes, the windings comprising:

- 5 a first winding having four coil sections spaced in the slots of the stator and configured to create alternating poles;
- a second winding having two coil sections, each aligned with opposing coil sections of the first winding;
- a third winding having two coil sections, each aligned with opposing coil sections of
- 10 the first winding;
- a fourth winding having six coil sections spaced in the slots of the stator, and arranged to create alternating poles;
- a first switch having a 4/8 pole position and a 6 pole position;
- a second switch having a 6/8 pole position and a 4 pole position; and
- 15 a third switch having a 4/6 pole position and an 8 pole position;
- the switches, when in their respective 4 pole positions connecting first winding in series with the parallel combination of the second and third windings to operate in a four pole conventional mode, and when in their respective eight pole positions connecting the second and third windings in series to operate in an eight pole consequent mode; and when in their
- 20 respective 6 pole positions connecting the fourth winding to operate in the six pole mode.

7. A single-phase, three speed induction motor comprising a stator, a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and a plurality of windings in the slots configurable to operate in four, six, and eight pole modes, the windings comprising:

- 5 a first winding having four coil sections spaced in the slots of the stator and configured to create alternating poles;
- a second winding having two coil sections, each aligned with opposing coil sections of the first winding;
- a third winding having two coil sections, each aligned with opposing coil sections of
- 10 the first winding;
- a fourth winding having six coil sections spaced in the slots of the stator, and arranged to create alternating poles;

the first, second, and third windings being configured to be connected to operate in a four pole conventional mode, and the second and third windings being configured to be
15 connected to operate in an eight pole consequent mode.

8. A single-phase, three speed induction motor comprising a stator, a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and a plurality of windings in the slots configurable to operate in four, six, and eight pole modes, the windings comprising:

- 5 a first winding having four coil sections spaced in the slots of the stator and configured to create alternating poles;
- a second winding having two coil sections, each aligned with opposing coil sections of the first winding;
- a third winding having two coil sections, each aligned with opposing coil sections of
10 the first winding;
- a fourth winding having six coil sections spaced in the slots of the stator, and arranged to create alternating poles;
- first and second switches for selectively connecting the first winding in series with the parallel combination of the second and third windings to configure the first, second, and
15 third windings to operate in a four pole conventional mode, and for selectively connecting the second and third windings in series to configure the second and third being configured to be connected to operate in an eight pole consequent mode.

9. A single phase, three-speed induction motor comprising a stator and a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and a plurality of windings in the slots for operating at at least three different pole speeds, at least two of the windings being used in their entireties to operate at at least two of the at least
5 three speeds, the at least two windings being connected to form a first number of conventional poles in the higher speed, and being connected to form a second number of consequent poles in the lower speed.

10. A single phase, three-speed induction motor comprising a stator and a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and at first, second, third and fourth windings in the slots for operating at at least three different pole speeds, the first, second, and third windings being connectable in a first mode
5 of operation to form a first number of conventional poles; the second and third windings being connectable in a second mode of operation to form a second number of consequent

poles, and the forth winding being connectable in a third mode of operation to form a third number of poles, the first, second, and third numbers all being different so that the speed in the first, second and third modes of operation are different.

11. The motor according to claim 10, wherein the second number of poles is double the first number of poles.

12. The motor according to claim 11, wherein the second number of poles is eight, and the first number of poles is four.

AMENDED CLAIMS

[received by the International Bureau on 02 November 1999 (02.11.99);
original claims 6, 8 and 10 amended; remaining claims unchanged (3 pages)]

5. The motor according to claim 4 further comprising an auxiliary winding having six coil sections for starting the motor.

6. A single-phase, three speed induction motor comprising a stator, a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and a plurality of windings in the slots configurable to operate in four, six, and eight pole modes, the windings comprising:

5 a first winding having four coil sections spaced around the circumference of the stator and configured to create alternating poles;

a second winding having two coil sections, each aligned with opposing coil sections of the first winding;

10 a third winding having two coil sections, each aligned with opposing coil sections of the first winding;

a fourth winding having six coil sections spaced around the circumference of the stator, and arranged to create alternating poles; a first switch having a 4/8 pole position and a 6 pole position;

15 a second switch having a 6/8 pole position and a 4 pole position; and
a third switch having a 4/6 pole position and an 8 pole position;

the switches, when in their respective 4 pole positions connecting the first winding in series with the parallel combination of the second and third winding to operate in a four pole conventional mode, and when in their respective eight pole positions connecting the second and third windings in series to operate in an eight pole consequent mode; and when in their respective 6 pole positions connecting the fourth winding to operate in the six pole mode.

25 7. A single-phase, three speed induction motor comprising a stator, a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and a plurality of windings in the slots configurable to operate in four, six, and eight pole modes, the windings comprising:

a first winding having four coil sections spaced around the circumference of the stator and configured to create alternating poles;

a second winding having two coil sections, each aligned with opposing coil sections of the first winding;

30 a third winding having two coil sections, each aligned with opposing coil sections of the first winding;

a fourth winding having six coil sections spaced around the circumference of the stator, and arranged to create alternating poles;

35 the first, second, and third windings being configured to be connected to operate in a four pole conventional mode, and the second and third windings being configured to be connected to operate in an eight pole consequent mode.

8. A single-phase, three speed induction motor comprising a stator, a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and a plurality of windings in the slots configurable to operate in four, six, and eight pole modes, the windings comprising:

5 a first winding having four coil sections spaced around the circumference of the stator and configured to create alternating poles;

a second winding having two coil sections, each aligned with opposing coil sections of the first winding;

10 a third winding having two coil sections, each aligned with opposing coil sections of the first winding;

a fourth winding having six coil sections spaced around the circumference of the stator, and arranged to create alternating poles;

15 first and second switches for selectively connecting the first winding in series with the parallel combination of the second and third windings to configure the first, second, and third windings to operate in a four pole conventional mode, and for selectively connecting the second and third windings in series to configure the second and third winding being configured to be connected to operate in an eight pole consequent mode.

9. A single phase, three-speed induction motor comprising a stator and a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and a plurality of windings in the slots for operating at at least three different pole speeds, at least two of the windings being used in their entireties to operate at at least two of the at least 5 three speeds, the at least two windings being connected to form a first number of conventional poles in the higher speed, and being connected to form a second number of consequent poles in the lower speed.

10. A single phase, three-speed induction motor comprising a stator and a rotor rotatably mounted within the stator, the stator comprising a core having a plurality of slots, and with first, second, third and fourth windings in the slots for operating at at least three different pole speeds, the first, second, and third windings being connectable in a first mode 5 of operation to form a first number of conventional poles; the second and third windings being connectable in a second mode of operation to form a second number of consequent

poles, and the forth winding being connectable in a third mode of operation to form a third number of poles, the first, second, and third numbers all being different so that the speed in the first, second and third modes of operation are different.

11. The motor according to claim 10, wherein the second number of poles is double the first number of poles.

12. The motor according to claim 11, wherein the second number of poles is eight, and the first number of poles is four.

1 / 6




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6

INTERNATIONAL SEARCH REPORT

International Application No

PCT/US 99/11235

A. CLASSIFICATION OF SUBJECT MATTER
IPC 6 H02K17/06

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 6 H02K H02P

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 3 350 614 A (HAROLD C STOUT) 31 October 1967 (1967-10-31) the whole document ---	1-12
A	US 3 887 854 A (PARKS WALTER K) 3 June 1975 (1975-06-03) ---	
A	US 3 233 160 A (GORDON H RAWCLIFFE) 1 February 1966 (1966-02-01) -----	

☐ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier document but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

"&" document member of the same patent family

Date of the actual completion of the international search

26 August 1999

Date of mailing of the international search report

02/09/1999

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Ramos, H

INTERNATIONAL SEARCH REPORT

information on patent family members

International Application No

PCT/US 99/11235

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 3350614 A	31-10-1967	NONE	
US 3887854 A	03-06-1975	NONE	
US 3233160 A	01-02-1966	NONE	